



**ENERGY SAVING
ECO MODE
SET UP**



**2/200
cd/m²**

DIP SWITCH FEATURES No.1-4 / DIP PREPÍNAČ č.1-4 - FUNKCIE

SELF-CONTAINED BATTERY VERSIONS

**NORMAL MODE
230V MAINS**

**EMERGENCY
BATTERY MODE**

**+2xLED
BOTTOM LEDs
ACTIVATION**



+2xBOTTOM LEDs ACTIVATION in 230V
ON - ACTIVATED
OFF - DEACTIVATED



DEFAULT SETT./ PREDNASTAVENÉ
Full Power



ECO MODE 50% (in 230V mode)
EMERGENCY MODE LEGEND
BRIGHTNESS > 200cd/m²



ECO MODE 25% (in 230V mode)
EMERGENCY MODE LEGEND
BRIGHTNESS > 200cd/m²



ECO MODE 10% (in 230V mode)
EMERGENCY MODE LEGEND
BRIGHTNESS > 200cd/m²



ENERGY SAVING (in emerg.mode)
LEGEND BRIGHTNESS > 2cd/m²
JAS PIKTOGRAMU > 2cd/m²



ENERGY SAVING (in emerg.mode)
ECO MODE 50% (in 230V mode)
LEGEND BRIGHTNESS > 2cd/m²




ENERGY SAVING (in emerg.mode)
ECO MODE 25% (in 230V mode)
LEGEND BRIGHTNESS > 2cd/m²



ENERGY SAVING (in emerg.mode)
ECO MODE 10% (in 230V mode)
LEGEND BRIGHTNESS > 2cd/m²



**INSTALLATION
MODE
SET UP**



DEFAULT / PREDNASTAVENÉ
OFF - ACTIVATED
ON - DEACTIVATED

**M /
NM**

**NON-MAINTAINED /
MAINTAINED
MODE
SET UP**



DEFAULT / PREDNASTAVENÉ
ON - MAINTAINED
OFF - NON-MAINTAINED

**AT /
ATXL**

**AUTOTEST /
CENTRALTEST
MODE
SET UP**



DEFAULT / PREDNASTAVENÉ
OFF - AUTOTEST
ON - CENTRALTEST

CBS CENTRAL BATTERY VERSIONS

**CBS CENTRAL
BATTERY**

**1 LUX
ESCAPE ROUTE
APPLICATION**



FULL POWER
PLNÝ VÝKON



FULL POWER
LEGEND BRIGHTNESS > 200cd/m²
JAS PIKTOGRAMU > 200cd/m²




ECO MODE 50%



ECO MODE 25%



ECO MODE 10%
LEGEND BRIGHTNESS > 2cd/m²
JAS PIKTOGRAMU > 2cd/m²



ONLY FOR CBS VERSIONS
ON - +2 BOTTOMLEDs CONTROL
OFF - DIMMING

ONLY FOR CBS VERSIONS
ON - NEGATIVE
OFF - POSITIVE

**TO SEE THE CHANGE EITHER PUSH THE TEST BUTTON OR
DISCONNECT THE FIXTURE FROM BOTH THE MAINS 230V AND BATTERY**

Po prestavení stlačte TEST alebo odpojte batériu a pripojenie na sieť na aktiváciu zmeny